

LW26 Universal Changeover Switch



General

LW26 Series Universal changeover switch mainly used for AC 50/60Hz, rated voltage up to 380V and below, DC voltage up to 220V, rated current to 160A electrical circuit for manually infrequent making or breaking the circuit for the purposes of control and conversion ,can also controlling three-phase asynchronous motors and circuit directly as the purposes of master control and measurement. The products widely used, instead of the various national switch, can be used as the circuit control switch, measuring equipment switches, motor control switches and the master control switch, and welding machine switch and so on. standard: IEC60947-3

Operating conditions

1. The ambient air temperature does not exceed +40°C, the average temperature within 24 hours and not more than +35°C.The ambient air temperature is not lower than -5°C.
2. Installation site altitude does not exceed 2000m
3. The relative humidity of the air no more than 50% when the maximum temperature is +40°C and at a lower temperature allows a higher relative humidity, such as when temperature is 20°C the relative humidity reaches 90%.
4. Special measures should be taken for condensation occassionally due to temperature changes.

Type designation

For use to master control

LW26	Rated thermal current	Poles	Station
LW26	20	2P	2
Universal changeover switch	10:10A	2P	2
	20:20A	3P	3
	25:25A	4P	4
	32:32A	5P	5
	63:63A	6P	6
	125:125A		7
	160:160A		
	200:200A		
	315:315A		
	400:400A		
		V: Voltage meter A: Ammeter	

Note: If there are special wiring requirements, please provide the wiring diagram or contact us

Industrial equipment and switches

LW26 Universal Changeover Switch

General

The following table shows the main technical parameters of the transfer switch

Table 2

Model	Ith A	Ui V	Ue V	AC-21A	AC-22A	AC-23A		AC-2		AC-3		AC-4		AC-15	DC-13
				Ie A	Ie A	Ie A	P kW	Ie A	P kW	Ie A	P kW	Ie A	P kW	Ie A	Ie A
LW26-10	10	660	240		10	7.5	1.8	7.5	2.5	5.5	1.5	1.75	0.37	2.5	
	10	660	440		10	7.5	3.0	7.5	3.7	5.5	2.2	1.75	0.55	1.5	
LW26-20	20	660	440		20	15	7.5	15	7.5	11	5.5	3.5	1.5	4	
	20	660	240											5	1
	20	660	120												5
LW26-25	25	660	440		25	22	11	22	11	15	7.5	6.5	3	5	
	25	660	240											8	1.5
	25	660	120		32	30	15	30	15	22	11	11	5.5		9
LW26-32	32	660	440											6	
	32	660	240											14	11
	32	660	120												25
LW26-63	63	660	440		63	57	30	57	30	36	18.5	15	7.5		
	63	660	120												55
LW26-125	125	660	440		125	90	45	90	45	75	30	30	12		90
LW26-160	160	660	440		160	135	75	135	55	95	37	55	15		110

The following table shows the relevant dimension of the transfer switch

Table 3

Model	Panel Specification	Dimensions(mm)				Model	Panel Specification	Dimensions(mm)			
		A	B	C	L			A	B	C	L
LW26-10	M0 Square	30	30	26	22+8n	LW26-32	M2 Square	64	64	58	29.2+12.8n
LW26-20	M1 Square	48	48	43	22+9.6n		M2 Rectangle	64	80	58	29.2+12.8n
	M2 Square	64	64	43	25+9.6n		M3 Square	88	88	58	29.2+12.8n
LW26-20c	M2 Rectangle	64	80	43	25+9.6n	LW26-63	M2 Square	64	64	66	29.2+21.5n
	M2 Square	64	64	60	42.5+12.6n		M2 Square	64	80	66	29.2+21.5n
	M2 Rectangle	64	80	60	42.5+12.6n		M3 Square	88	88	66	29.2+21.5n
LW26-25	M3 Square	88	88	60	42.5+12.6n	LW26-125	M3 Square	88	88	84	35+26.5n
	M1 Square	48	48	45.2	23+12.8n	LW26-160	M3 Square	88	88	88	35+32.5n
	M1 Rectangle	48	60	45.2	23+12.8n	LW26-315	M4 Square	130	130	126	39.5+38.5n
	M2 Square	64	64	45.2	26.5+12.8n						
	M2 Rectangle	64	80	45.2	26.5+12.8n						

